



SOUND ASSOCIATES, INC.

INFRARED PENDANT RECEIVER

- SA1502P (2-CHANNEL, STEREO)

The Sound Associates SA1502P receiver is a wireless 2-channel, stereo infrared pendant receiver designed for professional applications. While other wireless receivers suffer from poor reception and fidelity, Sound Associates' sophisticated receiving circuitry with its dual receiving diodes and infrared transparent case is extremely sensitive.

The SA1502P is designed to receive a frequency modulated signal of 2.3 MHz (channel 1), 2.8 MHz (channel 2) or both 2.3 MHz (left) and 2.8 MHz (right) for stereo.

Compatible with most infrared transmission systems currently in use, the SA1502P is compliant with standards outlined in the Americans With Disabilities Act (ADA) and can be used in conjunction with the Sound Associates SA650NIL neck induction loop to supplement personal hearing aids with a telecoil or T-switch setting. Perfect for stereo or mono headphones, it can also accommodate most Cochlear implant patch cables with a 3.5 mm plug.

This lightweight receiver is powered by a rechargeable battery and can be worn around the neck, pendant-style (with supplied lanyard) or clipped on a pocket.

Sound Associates also offers a 2-channel/stereo pendant receiver, in 95kHz and 250 kHz model no. SA652P



SA1502P 2-Channel Stereo Receiver
Ch. 1 - 2.3 MHz, Ch. 2 - 2.8 MHz
shown with SA600E Ear Surround, sold separately.
Also compatible with SA650NIL Neck Induction Loop

Features:

- Two selectable channels for multi-language interpretation or stereo audio enhancement.
- Unit automatically turns on when 3.5 mm jack is inserted. (LED will illuminate.)
- Two receiving diodes and infrared transparent case for wider scope of coverage and greater sensitivity.
- Uses lanyard or pocket spring clip on back to wear in a variety of ways.
- Rechargeable battery that charges in a 115 volt AC outlet (with adapter).
- Recommended for use with Sound Associates SA650NIL Neck Induction Loop.
- Slide volume and channel selection for simple operation.
- Full one-year warranty.



SOUND ASSOCIATES, INC.

SA1502P Receiver

includes (1) SA505 Rechargeable Battery and requires a neck induction, headphone or earpiece with 3.5 mm jack (sold separately)



Technical Specification:

Modulation	Ch. 1: 2.3 MHz, Ch. 2: 2.8 MHz or Stereo: (tip - 2.3 MHz), (ring - 2.8 MHz) WB
Infrared Wavelength	880 - 1200 nm
Output	approximately 0.6 V
Frequency Response	100 Hz - 15 kHz
Operation time (fully charged battery)	Approx 8 hours
Charging Time	14 hours
Battery	2.4 V rechargeable NiMH
Dimensions folded	2.75" x 2.25" x 1.25" deep
Weight	1.8 oz (2.5 oz. with battery)
Power indicator	red LED on top of unit

Accessories:

SA505	Rechargeable NiMH battery (included)	SA1910	Smart Charger: 10 position battery charger
SA650NIL	Neck Induction Loop	SA1920	Smart Charger: 20 position battery charger
SA600E	Single Ear Surround	SA1950	Smart Charger: 50 position battery charger
DC24	Distribution cabinet: 24 position	BC01	Individual battery charging adapter
DC50	Distribution cabinet: 50 position		
CC1A	Individual carrying case		
CC10	Carrying case: 10 position		

Warranty

The SA1502P pendant receiver and the SA505 rechargeable battery are covered by a full one-year warranty, from the original date of purchase, against defects in workmanship or materials. If either component fails due to defects in craftsmanship or materials, we will repair or replace the component without charge. The factory warranty does not cover malfunctions due to abuse or operation other than specified.

424 West 45th Street, New York, NY 10036 TEL: 212-757-5679

TOLL FREE 888-772-SOUND (888-772-7686)

www.soundassociates.com